

Datavideo SE-1200MU

ProdCode: DATASE1200MU

6 Input Rackmount HD Mixer



[Download Images] (.zip file)

Features

- 6 video inputs (SDI x 4 + HDMI x 2)
 - Frame Sync on each input
- Flexible Mix/Effects Processor with
 - 2 Upstream Keyers, supporting Chroma Key & Linear/Luma Key
 - 2 DSK, supporting Linear & Luma Key Modes
 - 1 PIP (assignable to any of the 4 keyers
 - Wipe Generator: 32 Wipe Patterns, including Circle & Heart | Borders & Softness Control
 - Wipe, Mix & Cut Transitions
 - Full M/E Preview function
- Any Input (1-6) can be used as a Frame store (Stills Store): Upto 24 images stored on SD Card
- Assignable Outputs
 - Each SDI output can be switched in the Menu as:
 - PROGRAM (w/ DSK)
 - Clean PROGRAM (w/o DSK)
 - Clean PREVIEW (w/o DSK)

- MULTISCREEN
- Input 1-6
- XPT (Cross Point Assignment)
- PC control
- Control Switcher via USB / Laptop keyboard
- Control with optional RMC-260
- Remote streaming of Multi view out using built-in Motion JPEG Streaming processor
- Tally output
- GPI output
- 1U rack mount

Whether you are filming a seminar or conference, conducting a live outside broadcast or shooting inside a production studio, the Datavideo SE-1200MU HD video switcher enables you to switch seamlessly between video sources and blend high-quality digital content on the fly.

SE-1200MU a small, portable computer controlled 1RU rack mountable switcher. It features a 6-Channel HD video input that is incredibly reliable, unlike PC-based systems that are prone to crashing mid production.

SE-1200MU streams out multi-view screen video in real-time to a control PC for monitoring and control remotely. It is designed to be fully controlled from any Windows Laptop / PC and Android tablet / iPad / Mac with the included SE-1200 software control panel.

SE-1200MU includes four SDI and two HDMI inputs with embedded audio and an internal frame synchronizer so you can use sources without gen-lock such as consumer HDMI cameras or even computers for live PowerPoint™ presentations.

Two assignable SDI and two HDMI outputs for connecting an HD recorder, monitor and a streaming encoder, plus two Balanced XLR audio inputs for connecting an external audio mixers. Other features include chromakey, lumakey, DSK, PIP, still stores, audio delay, tally and RJ-45/RS-232 remote control interface.

Users have the option to link a laptop to the switcher unit via USB, for a fast, secure connection. This gives plug and play control over all the functions of the mixer, with no need to configure the computer's IP or network settings.

In the box:

- 1 x SE-1200MU
- 1 x AD Switch DC 12V

Need Further Support?

If you have any questions or require additional support regarding this product release, please do not hesitate to contact us. Our team is here to assist you with any inquiries or provide further information or marketing collateral as needed.

Contact Us:

- Marketing marketing@holdan.co.uk
- Sales sales@holdan.co.uk
- Technical Enquiries techsales@holdan.co.uk
- Request Demo product loans demo@holdan.co.uk

We value your partnership and are committed to ensuring a successful product launch. Thank you for your continued support.