

Sonnet Echo 20 Thunderbolt 4 SuperDock

ProdCode: SONECHODK20T4

Universal Thunderbolt 4 Dock with Three Thunderbolt 4 Ports, M.2 SSD Slot, HDMI 2.1 Port, 2.5Gb Ethernet Port, Eight 10Gbps USB Ports, and More



[\[Download Images\]](#) (.zip file)

Features

- Universal Thunderbolt 4 Dock with Three Thunderbolt 4 Ports, M.2 SSD Slot, HDMI 2.1 Port, 2.5Gb Ethernet Port, Eight 10Gbps USB Ports, and More
- **One Cable Peripheral Connection**
Instant access – plug in all your peripherals into the Echo dock and connect your computer to the dock with the included Thunderbolt 4 cable
- **Twenty Interfaces**
SuperDock includes three Thunderbolt 4, four USB 3.2 Gen 2 Type A, and four USB 3.2 Gen 2 Type-C charging ports; HDMI port; RJ45 2.5 Gigabit Ethernet; 3.5mm combo audio; 3.5mm microphone; line-level R+L RCA audio out; SD 4.0 card slot; and M.2 SSD slot
- **Two Thunderbolt 4 Ports for Peripherals**
Connect two Thunderbolt peripherals directly (with support for daisy chaining additional peripherals). Also support USB4 and USB 3 devices, plus displays
- **M.2 NVMe SSD Slot**
Add up to 8TB of storage inside (SSD sold separately); data transfer speeds up to 800MB/s for fast media storage and Time Machine backups

- **10Gbps USB Type-C Charging Ports**
Four USB 3.2 Gen 2 USB-C ports support the USB Type-C Charging spec and provide up to 7.5W of power each, supporting super-fast USB NVMe SSDs at up to full speed, and device charging too
- **Powerful 10Gbps USB Type A Ports**
Four USB 3.2 Gen 2 USB-A ports provide up to 7.5W of power each, supporting super-fast USB NVMe SSDs at up to full speed
- **Built-in HDMI Port**
Connect an 8K @60Hz HDMI display directly, no adapter required
- **Support for 4K, 5K, 6K and 8K @60Hz Displays**
Depending on your computer, supports up to two 6K displays or a single 8K display
- **Connect Another Display via Thunderbolt**
Connect a Thunderbolt or USB-C display directly. Supports an HDMI or DisplayPort display with a Thunderbolt-compatible adapter (sold separately)
- **Charge Your Laptop**
Provides up to 100W through the included Thunderbolt 4 cable to power and charge your laptop
- **More Audio I/O**
3.5mm stereo headset jack on the front panel. Separate left/right channel RCA line out jacks that deliver a clean signal to powered speakers or an amplifier, plus a 3.5mm microphone jack populate the back panel
- **Fast SD Card Slot**
Compatible with SD™, SDHC™, and SDXC™ memory cards; supports 320 MB/s read speeds with UHS-II SDXC cards. Also supports microSD™ cards when used with adapter
- **Apple M Series Compatible**
Supports all M series Macs
- **Intel® Mac and Windows Compatible**
Supports Thunderbolt 3 Macs all Thunderbolt 4 Windows computers, and late model Thunderbolt 3 Windows computers
- **Apple M series iPad Pro Compatible**
Supports all M series iPad Pro tablets

Expand Your Connectivity to the Max

More connections than you expect from a Thunderbolt™ dock – NVMe SSD storage capability, an HDMI port, ultra-fast 2.5 Gigabit Ethernet support, and more! With this superdock, a single cable connects your computer to your digital world. The Sonnet Echo™ 20 Thunderbolt 4 SuperDock is your universal docking station for today and tomorrow.

Maximum Value and Connectivity Docking Station

- Thunderbolt 4: Directly attach two Thunderbolt peripherals – and daisy chain up to a total of 5 devices
- 100W Power Delivery: Connect and charge your laptop with up to 100W Power Delivery
- SSD Storage: Install an M.2 NVMe SSD; add up to 8TB of fast storage!
- Direct 8K HDMI: Connect an 8K @60Hz HDMI display directly to the dock; no adapter required
- 8K Support: Connect up to two 6K displays; or a single display up to 8K!
- USB 3: Plug in up to 10 USB 3 devices via Type A and Type-C ports
- 2.5Gb Ethernet: Link to an Ethernet network at 2.5 Gigabit speed!
- Device Charging: Charge your phone
- Headset: Plug in your headset
- Microphone: Plug in your microphone
- Powered Speakers: Connect your powered speakers
- SD Cards: Read your SD cards

Plug In Your Peripherals and Power Your Computer with One Cable

Connect your Thunderbolt devices, monitor(s), USB peripherals, powered speakers, and Ethernet cable to the dock and then link them all to your computer with a single Thunderbolt cable. Got a laptop computer? You can keep its power adapter in your bag because Echo 20 Thunderbolt 4 SuperDock will power it with up to 100W of charging power. When it is time to leave, just unplug the Thunderbolt cable, grab your computer, and go.

Internal SSD Expansion Slot

The built-in M.2 NVMe SSD slot enables you to add up to 8TB of SSD storage (SSD sold separately) to your system without connecting a storage device to the Echo dock or the computer. SSD installation is an easy task – simply remove the two screws securing a bottom panel cover, insert the SSD, and reinstall and secure the bottom cover. Transfer and access data at up to 800 MB/s, and effortlessly store large files, media libraries, or your Time Machine® backups.

SSD sold separately

Onboard HDMI Display Support

Echo 20 Thunderbolt 4 SuperDock features a built-in HDMI port, enabling you to plug in an HDMI display directly to the dock.

Faster Ethernet Transfers Across Existing Cabling

Featuring 2.5 Gigabit Ethernet, Echo 20 Thunderbolt 4 SuperDock supports a 2.5 Gb/s link speed over common Cat 5e (or better) cabling when used with a compatible Ethernet switch or NAS with 2.5Gb Ethernet support, saving you the cost of another adapter. You can get great performance gains – 250 percent the speed of Gigabit Ethernet – without rewiring! Need to connect to a switch without 2.5Gb Ethernet support? The Sonnet dock also supports 1Gb/s and 100Mb/s link speeds.

Dual Downstream Thunderbolt Ports – Simple Comprehensive Connectivity for Work and Play

Echo 20 Thunderbolt 4 SuperDock features three Thunderbolt 4 ports: one for connection/power to your computer – ideal for Mac and Windows laptop computers with only one or two Thunderbolt ports because you can connect and charge on the same port – plus two for directly connecting Thunderbolt peripheral devices.

The Thunderbolt peripheral ports also support USB4 and USB 3 peripherals, and even provide 15W power each to support the most demanding bus-powered Thunderbolt and USB peripherals. If your computer supports it, you can even connect another display.

Powerful 10Gbps USB-A and USB-C Ports

Echo 20 Thunderbolt 4 SuperDock features four USB 3.2 Gen 2 (10Gbps) Type A ports and four USB 3.2 Gen 2 Type-C ports – two each on the front and back – to support super-fast USB NVMe SSDs at up to full speed. And unlike some other docks, Echo 20 doesn't skimp on power either – each port provides up to 7.5W to ensure that drives with higher peak power requirements can mount and operate without fail. An added benefit for the USB-C ports is they support the Type-C Charging spec, enabling the dock to charge devices even when the computer is off, sleeping, or disconnected.

Thunderbolt Certified for Mac, Windows, Chromebook, and iPad Pro

Echo 20 Thunderbolt 4 SuperDock is certified for use with Apple M series Macs; Thunderbolt 3 Intel Macs; Thunderbolt 4 or USB4 Windows computers; Thunderbolt 3 Windows computers with an Intel 8th Gen (2018) or newer CPU; Thunderbolt 4/USB4 Chromebook; and M series iPad Pro.

Single 8K or Dual 6K 60Hz Displays

Depending on your computer's video capability and whether you've connected a monitor to the built-in HDMI port, the Echo dock's Thunderbolt ports can support one (always 4K, 5K or 6K, up to 8K) monitor, or up to two 6K monitors; see Tech Specs.

You can plug in Thunderbolt 3 or 4, or USB-C monitors directly. Or, you may connect other display types (HDMI, DisplayPort, etc.) by using a Thunderbolt-compatible adapter (sold separately).

Leave the Charger In Your Backpack

Connected to your laptop computer with the included Thunderbolt 4 cable, Echo 20 Thunderbolt 4 SuperDock provides up to 100W of power (Power Delivery) from its rear-mounted Computer/Charging port, meaning it can power and charge your computer while connected, even when not in use, allowing you to leave your computer's power adapter packed away.

Dedicated RCA Audio Outputs

Echo 20 Thunderbolt 4 SuperDock features stereo RCA connections. RCA outputs provide consistent line-level audio, connecting your sweet music library to your pair of powered speakers. RCA outputs are also ideal for direct connection to a receiver, power amplifier, or mixer.

Fast UHS-II SD 4.0 Card Reader

The included SD card slot is compatible with SD™, SDHC™, and SDXC™ memory cards, and supports 320 MB/s read speeds with UHS-II SDXC cards to quickly offload images and video. microSD cards are also supported when used with adapters commonly included with the cards.

Thunderbolt 4 Cable and ThunderLok 4 Included

Sonnet includes a Thunderbolt cable and security clip with the Echo 20 SuperDock. The Thunderbolt cable supports Thunderbolt's full 40Gbps bandwidth and 100W power charging capability. ThunderLok™ 4 Thunderbolt connector retainer clip prevents accidental cable disconnections by sliding easily over one end of the cable and securing directly to the dock with a thumbscrew. Because of its unique design, ThunderLok remains on the cable, so it won't get lost when not in use.

Kensington Lock Ready

With up to 8TB of valuable data inside, you may want to secure the Echo dock with a Kensington® Lock (sold separately).

In the box:

- Echo 11 Thunderbolt 4 HDMI Dock

- Power adapter
 - Power cord
 - 0.7-meter Thunderbolt 4 cable
 - ThunderLok 4 Thunderbolt connector retainer clip(5)
 - Documentation
-

Need Further Support?

If you have any questions or require additional support regarding this product release, please do not hesitate to contact us. Our team is here to assist you with any inquiries or provide further information or marketing collateral as needed.

Contact Us:

- Marketing - marketing@holdan.co.uk
- Sales - sales@holdan.co.uk
- Technical Enquiries - techsales@holdan.co.uk
- Request Demo product loans - demo@holdan.co.uk

We value your partnership and are committed to ensuring a successful product launch. Thank you for your continued support.